


Bussmann series arc flash relay system



EAFR-110F



EAFR-101

Contents

1. Introduction	1
2. Overview	1
2.1 Speed	1
2.2 Flexibility	1
2.3 Reliability	1
2.4 Typical applications	1
3. Features	1
3.1 Protection features	1
3.2 Current sensing	1
3.3 Light sensing	1
3.4 Indication	1
3.5 Relay outputs	2
3.6 Self monitoring	2
3.7 Breaker failure	2
3.8 Communications	2
4. Bussmann series arc flash relay modules	5
5. Dimensions	6
6. Bussmann series arc flash relay sensors	8
7. Technical data	9
7.1 Protection stages	9
7.2 Current measuring circuits	9
7.3 Trip relays T1, T2, T3, and T4	9
7.4 High speed outputs HSO1 and HSO2	9
7.5 Binary output BO1	9
7.6 Binary inputs BI1 and BI2	9
7.7 Disturbance tests	9
7.8 Voltage tests	9
7.9 Mechanical tests	9
7.10 Casing and package	10
7.11 Environmental conditions	10
7.12 Approvals	10
8. Ordering codes	10
8.1 EAFR relay codes	10
8.2 EAFR-0x arc sensors	11

1. Introduction

Eaton's Bussmann™ series arc flash relay (EAFR) system is a combination of arc flash relay modules and sensors designed to detect and clear arc flash events in low and medium voltage electrical assemblies.

An arc fault is the most devastating type of fault in medium voltage (MV) and low voltage (LV) switchgear. If an arc fault occurs, the Bussman series EAFR system reduces arc energy by quickly clearing the current feeding the arc.

The Bussmann series EAFR system can measure both light and current to eliminate nuisance operation. In addition, its modular design makes it an excellent candidate for both new and retrofit installations.

2. Overview

2.1 Speed

As fast as 2 ms operating time

2.2 Flexibility

- Easy adaptation to any switchgear and trip scheme
- Variety of arc sensors available
- Long distance possible between units
- Practically an unlimited number of units can be interconnected in one system

2.3 Reliability

- Standard copper wire for communication between units
- Superior isolation levels for external disturbances - tested at the highest EMC classes
- Full internal monitoring of all system components and interconnections

2.4 Typical applications

- Low voltage switchgear/switchboards
- Medium voltage switchgear
- Low/medium voltage motor control

3. Features

3.1 Protection features

The Bussmann series EAFR system is a sophisticated micro-processor based arc flash protection system with combined current and arc sensing. Combined current and arc sensing provides an integrated dual trip criteria. It is designed to minimize the damage caused by an arcing fault (arc flash) by tripping the circuit breaker sourcing the fault current.

- Three phase instantaneous overcurrent elements (50P) (permissive only with light input)
- Ground instantaneous overcurrent element (50G) (permissive only with light input)
- Breaker failure (50BF)

3.2 Current sensing

The main units EAFR-110F and EAFR-110P each contain four current transformer inputs that provide sensing for the phase and ground instantaneous overcurrent elements. These elements act as a permissive for the light sensing inputs so that when they are incorporated into the scheme, both current and light must be present to initiate a trip command. This current information can be shared with downstream modules as well.

3.3 Light sensing

Arc flash light can be collected by either point sensors or fiber loop sensors. Up to 12 point sensors or 3 loop sensors can be connected to each module. Light sensing can initiate a breaker trip independent of current if desired. Because point sensors are interconnected with copper wire, they can provide a much better installation for electrical OEMs where the system can be fully wired and tested in the factory. Sensor wiring allows daisy chaining up to three sensors over a distance of 100 meters. Fiber loop sensors are available in either plastic or glass versions. Point sensors are available in multiple sensitivity levels with the 8K lux sensor being suitable for most applications.

- Point sensors (up to 12 sensors per module)
- Fiber loop sensors (up to 3 sensors per module)

3.4 Relay outputs

- Four trip relays per module (7 ms)
- Two high speed outputs (2 ms – EAFR-110P, EAFR-110F)
- System failure relay

3.5 Indication

- Power available LED
- System health LED
- Trip relay activation LEDs
- Sensor channel activation LEDs
- Overcurrent element pickup LEDs

3.6 Self monitoring

Complete system self monitoring provides the highest level of dependability by continuously monitoring all internal system functions along with external connections between modules, light sensors or loops and current transformers.

3.7 Breaker failure

The circuit breaker failure protection (CBFP) is initiated when a light signal and second trip criteria signal (e.g. over-current), if applicable, is active for above the set CBFP time of either 100 or 150 ms. The trip relay T2 and binary output BO1 will operate after the set time delay.

3.8 Communications

Because of the simplicity of the system, all monitoring is done through contact outputs on the modules. The advantage of this approach is that cybersecurity issues are non-existent.

3.9 Configuration

Easy configuration and setup with 4 dip switches to select one of many different standard sensor channel configurations for light or light & current tripping.

Figure 1. Double ended substation using point sensors




Figure 2. Double ended substation with selective feeder trip using point sensors





Figure 3. Double ended substation using fiber loop sensors



Legend:

- CBFP - Circuit Breaker Failure Protection
- HSO - High Speed Output
- T - Trip Output
- MT - Multi trip

4. Bussman series EAFR modules

Table 1. Arc flash relay modules

Features	EAFR-110F	EAFR-110P	EAFR-102	EAFR-101/D
3-Phase current detection	Yes	Yes	No	No
Ground current detection	Yes	Yes	No	No
Maximum point sensors	0	12	0	12
Maximum fiber loop sensors	3	0	3	0
High speed outputs (2 ms)	2	2	0	0
Trip relays (7 ms)	4	4	4	4

Figure 5. EAFR-110



Figure 6. EAFR-101/102



Figure 7. EAFR-101D



5. Dimensions

Figure 8. EAFR-110 dimensions in millimeters (inches) in 3D view



Figure 9. EAFR-110 cutout for panel mounting in millimeters (inches)




Figure 10. EAFR-102 dimensions in millimeters (inches) (side view)




Figure 12. EAFR-102 cut-out for panel mounting in millimeters (inches)





Figure 11. EAFR-101D dimensions in millimeters (inches) (side view)



6. Bussmann series arc flash relay sensors

Figure 13. EAFR-06 – arc light plastic fiber sensor




Figure 14. EAFR-07 – arc light glass fiber sensor



Figure 15. EAFR-01-A point sensor



Figure 16. Length of EAFR-01-A point sensor chain



7. Technical data

7.1 Protection stages

Trip time using HSO	2 ms*
Trip time using mechanical trip relays	7 ms*
Reset time (light stage)	1 ms
Reset time (over-current stages)	50 ms
Protection operational after power up	50 ms

* = Total trip time using arc light or phase/earth over-current from EAFR-110 and arc light.

7.2 Current measuring circuits

Nominal current	1 or 5 A
Rated frequency	2 to 1,000 Hz
Number of inputs	3 (phase) + 1 (earth)
Thermal withstand continuous	30 A
Thermal withstand 1 s	500 A
Thermal withstand 10 s	100 A
Phase over-current setting range	0.5 to 6 *In
Earth over-current setting range	0.05 to 2 *In
Measurement accuracy	10%
Rated AC burden (VA)	Input resistance 10 mΩ
Power consumption of current inputs circuit	<10 mΩ

7.3 Trip relays T1, T2, T3, and T4

Number	3 NO + 1 NC or 4 NO
Rated voltage	250 Vac/dc
Continuous carry	5 A
Make and carry for 0.5 s	30 A
Make and carry for 3 s	16 A
Breaking capacity DC, when time constant L/R = 40 ms	40 W; 0.36 A at 110 Vdc
Contact material	AgNi 90/10

7.4 High speed outputs HSO1 and HSO2

Number	2
Rated voltage	250 Vdc
Continuous carry	2 A
Make and carry for 0.5 s	15 A
Make and carry for 3s	6 A
Breaking capacity DC, when time constant L/R = 40 ms	1 A/110 W
Contact material	Semiconductor

7.5 Binary output BO1

Rated voltage	+24 Vdc
Rated current	20 mA (max)
Number of outputs	1

7.6 Binary inputs BI1 and BI2

Rated voltage	24
Rated current	3 mA
Number of inputs	2

7.7 Disturbance tests

EMC test	CE approved and tested according to EN 50081-2, EN 50082-2.
Emission	
- Conducted (EN 55011 class A)	0.15 - 30 MHz
- Emitted (EN 55011 class A)	30 - 1 000 MHz
Immunity	
- Static discharge (ESD) (according to IEC244-22-2 and EN61000-4-2, class III)	Air discharge 15 kV. Contact discharge 8 kV.
- Fast transients (EFT) (according to EN61000-4-4, class III and IEC801-4, level 4)	Power supply input 4 kV, 5/50 ns Other inputs and outputs 4 kV, 5/50 ns
- Surge (according to EN61000-4-5 [09/96], level 4)	Between wires 2 kV / 1.2/50 μs. Between wire and earth 4 kV / 1.2/50 μs.
- RF electromagnetic field test (according. to EN 61000-4-3, class III)	f = 80 to 1,000 MHz 10 V/m
- Conducted RF field (according to EN 61000-4-6, class III)	f = 150 kHz to 80 MHz 10 V

7.8 Voltage tests

Insulation test voltage acc - to IEC 60255-5	2 kV, 50 Hz, 1 min
Impulse test voltage acc - to IEC 60255-5	5 kV, 1.2/50 us, 0.5 J

7.9 Mechanical tests

Vibration test	2 to 13.2 Hz \pm 3.5 mm (0.14 in.) 13.2 to 100 Hz, \pm 1.0 g (0.04 oz)
Shock/bump test acc. to IEC 60255-21-2	20 g, 1,000 bumps/dir.

7.10 Casing and package

Protection degree (front)	IP 50
Protection degree (back)	IP 20
Dimensions - W x H x D mm (W x H x D in.)	102 x 157 x 164 mm (4.02 x 6.18 x 6.46 in.)
Package dimensions (W x H x D) mm (in.)	230 x 120 x 210 mm (9.06 x 6.18 x 6.46 in.)
Weight	0.7 kg (24.69 oz) 1.0 kg (35.27 oz) (with package)

7.11 Environmental conditions

Specified ambient service temp. range	-35 to +70°C (-31 to 158°F)
Transport and storage temp. range	-40 to +70°C (-40 to 158°F)
Relative humidity	Up to 97%

7.12 Approvals

UL/CUL Recognized File: E154862

8. Ordering codes

8.1 EAFR relay codes

Bussmann series catalog number	Part number description
EAFR-110P	Current, point sensor unit
EAFR-110F	Current, fiber loop sensor unit
EAFR-101	Point sensor unit
EAFR-101D	Point sensor unit, DIN rail mounted
EAFR-102	Fiber loop sensor unit

8.2 EAFR-0x arc sensors

Bussman series catalog number	Part number description
EAFR-01-A	Arc light point sensor - 8,000 Lux
EAFR-01-B	Arc light point sensor - 25,000 Lux
EAFR-01-C	Arc light point sensor - 50,000 Lux
EAFR-06-10	Arc light plastic fiber sensor - 10 m (32.81 ft)
EAFR-06-15	Arc light plastic fiber sensor - 15 m (49.21 ft)
EAFR-06-20	Arc light plastic fiber sensor - 20 m (65.62 ft)
EAFR-06-25	Arc light plastic fiber sensor - 25 m (82.02 ft)
EAFR-06-30	Arc light plastic fiber sensor - 30 m (93.43 ft)
EAFR-06-35	Arc light plastic fiber sensor - 35 m (114.83 ft)
EAFR-06-40	Arc light plastic fiber sensor - 40 m (131.23 ft)
EAFR-07-10	Arc light glass fiber sensor - 10 m (32.81 ft)
EAFR-07-15	Arc light glass fiber sensor - 15 m (49.21 ft)
EAFR-07-20	Arc light glass fiber sensor - 20 m (65.62 ft)
EAFR-07-25	Arc light glass fiber sensor - 25 m (82.02 ft)
EAFR-07-30	Arc light glass fiber sensor - 30 m (93.43 ft)
EAFR-07-35	Arc light glass fiber sensor - 35 m (114.83 ft)
EAFR-07-40	Arc light glass fiber sensor - 40 m (131.23 ft)
EAFR-07-45	Arc light glass fiber sensor - 45 m (147.64 ft)
EAFR-07-50	Arc light glass fiber sensor - 50 m (164.05 ft)
EAFR-08-10	Arc light glass fiber sensor (high temperature) - 10 m (32.81 ft)
EAFR-08-15	Arc light glass fiber sensor (high temperature) - 15 m (49.21 ft)
EAFR-08-20	Arc light glass fiber sensor (high temperature) - 20 m (65.62 ft)
EAFR-08-25	Arc light glass fiber sensor (high temperature) - 25 m (82.02 ft)
EAFR-08-30	Arc light glass fiber sensor (high temperature) - 30 m (93.43 ft)
EAFR-08-35	Arc light glass fiber sensor (high temperature) - 35 m (114.83 ft)
EAFR-08-40	Arc light glass fiber sensor (high temperature) - 40 m (131.23 ft)
EAFR-08-45	Arc light glass fiber sensor (high temperature) - 45 m (147.64 ft)
EAFR-08-50	Arc light glass fiber sensor (high temperature) - 50 m (164.05 ft)

The only controlled copy of this data sheet is the electronic read-only version located on the Eaton network drive. All other copies of this document are by definition uncontrolled. This bulletin is intended to clearly present comprehensive product data and provide technical information that will help the end user with design applications. Eaton reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Eaton also reserves the right to change or update, without notice, any technical information contained in this bulletin. Once a product has been selected, it should be tested by the user in all possible applications.

Eaton
1000 Eaton Boulevard
Cleveland, OH 44122
United States
Eaton.com

Bussmann Division
114 Old State Road
Ellisville, MO 63021
United States
Eaton.com/bussmannseries



© 2019 Eaton
All Rights Reserved
Publication No. 10961
August 2019

Eaton and Bussman are registered trademarks.

All trademarks are property of their respective owners.

For Eaton's Bussmann series
product information,
call **1-855-287-7626** or visit:
Eaton.com/bussmannseries

Follow us on social media to get the
latest product and support information.

